

1           **Amendments to the Claims:**

2           This listing of claims will replace all prior versions, and listings, of claims in the  
3 application:

4  
5           **Listing of Claims**

6           1. (Cancelled)

7           2. (Currently amended) A device operated by a user to monitor and indicate for  
8 ~~indicating~~ changes in ~~the monitored~~ resistance of a living body comprising:

9           a resistance measuring circuit having external leads for sensing the resistance of a  
10 living body placed across the external leads;

11           an amplifier coupled to the resistance measuring circuit for producing an analog  
12 measurement signal indicative of the sensed body resistance;

13           an indicator circuit for displaying visually perceivable indicia representative of  
14 sensed body resistance changes; and

15           a digital processing unit for digitizing and digitally processing the analog  
16 measurement signal in a manner that substantially offsets ~~the~~ effects of component aging,  
17 tolerances and temperature on ~~the accuracy of the~~ measurement signal accuracy

18           wherein the digital processing unit includes

19           means for substituting a plurality of electrical resistance values for sensing by the  
20 amplifier in lieu of a body resistance to produce measurement signals corresponding to  
21 simulated body resistance values, said plurality simulating a plurality of body resistance  
22 values,

23           means for digitizing the measurement signals corresponding to the simulated body  
24 resistance values, and storing in memory the resulting plurality of calibrated  
25 measurement values corresponding to the plurality of simulated body resistance values,

26           compensation means for computing, based on the stored calibrated measurement  
27 values, calibrated measurement values to be associated with respective additional body  
28 resistance values,

29           means for producing an indicator-driving series of digital difference values during  
30 the monitoring of the living body's resistance that represent the difference between the

1 monitored living body's digitized measurement ~~values~~ signals and a selected user-  
2 adjustable base value, the user-adjustable base value being selected by the user from  
3 calibrated measurement values,

4 manually positionable means operable by the user to select from the plurality of  
5 said base values ~~by adjusting the position of the manually positionable means~~, and  
6 sensitivity adjustment means for controlling the ~~magnitude of a~~ change in the indicator-  
7 driving difference values caused by a change in the monitored living body's sensed  
8 resistance, and

9 means applying an automatic correcting gain factor to the indicator-driving value  
10 as a function of the selected base value to produce the digitally processed measurement  
11 signal, the gain-applying means applying a first non-linear gain when the selected base  
12 value corresponds to a ~~very~~ low living body resistance value of less than approximately 5  
13 K-ohms ~~a first body-resistance value~~, and a second non-linear gain when the selected  
14 base value corresponds to a ~~very~~ high living body resistance value of more than 100 K-  
15 ohms ~~a second body-resistance value~~, the gain for the living body resistances values  
16 therebetween ~~between said first and second values~~ being essentially a constant, said first  
17 non-linear gain being more than said constant and increasing with decreasing base value,  
18 said second non-linear gain being less than said constant and increasing with increasing  
19 base value.

20  
21 3. (Previously presented) The device of Claim 2 wherein the first body-resistance  
22 value is approximately 5K-ohms.

23  
24 4. (Previously presented) The device of Claim 2 wherein the second body-  
25 resistance value is approximately 100K-ohms.

26  
27 5. (Original) The device of Claim 2 wherein the substituting means includes a  
28 multiplexer responsive to a plurality of selection signal values to respectively place a  
29 component in the resistance measuring circuit selected from the group consisting of (1)  
30 the external leads and (2) a respective one of a plurality of electrical resistors.

6. (Previously presented) The device of Claim 2 including means for automatically activating the substituting means upon powering-up of the device to produce the calibrated measurement values.

7. (Previously presented) The device of Claim 2 wherein the digital processing unit includes

means for subtracting the monitored body's electrical resistance value from the selected user-adjustable base value to produce an adjusted measurement signal as the measurement signal to the indicator means, and

an optical encoder coupled to the manually positionable means for producing the base value as a function of the position of the manually positionable means.

8. (Previously presented) The device of Claim 7 wherein the manually positionable means consists of a manually rotatable knob, and

the optical encoder includes a rotatable spindle coupled to said knob and means for producing a digital output signal indicative of the spindle's position of rotation.

9. (Original) The device of Claim 8 including means for adjusting the magnitude of the digital output signal from the optical output encoder prior to the subtraction of the monitored body's electrical resistance in the substantial accordance with the equation:

$$R_{TA} = \frac{3}{0.00016611111-0.00002555556(TA)}$$

where TA is the scale position of the manually positionable means, and

$R_{TA}$  is the value of the output signal.

1

2           10. (Original) The device of Claim 7 including  
3           means for repeatedly sampling the resistance value of the living body;  
4           means for subtracting each sampled value from the adjusted base value to obtain  
5           the measurement signal; and  
6           sensitivity adjustment means for coupling the measurement signal to the indicator  
7           means,  
8           the sensitivity adjustment means including means for multiplying the  
9           measurement signal by a gain factor which depends on the position of the manually-  
10          adjustable means.

11

12          11. (Previously presented) The device of Claim 2 wherein the substituting means  
13          includes a multiplexer responsive to a plurality of selection signal values to place  
14          respective electrical resistance values in the resistance measuring circuit in lieu of a  
15          living body resistance, and wherein  
16          the digital processing unit includes means for producing the selection signals to  
17          calibrate the device.

18

19          12. (Previously presented) The device of Claim 2 wherein the substituting means  
20          includes a multiplexer responsive to a plurality of selection signal values to place a  
21          component in the resistance measuring circuit selected from the group consisting of (1)  
22          the external leads and (2) a respective one of a plurality of electrical resistance values.

23

24          13. (Previously presented) The device of Claim 2 including means for  
25          automatically activating the substituting means, the digitizing means and the  
26          compensation means prior to the monitoring of the living body.

27

28          14. (Previously presented) The device of Claim 2 wherein the manually  
29          positionable means consists of a manually rotatable knob, and

1 an optical encoder including a rotatable spindle coupled to said knob to produce a  
2 digital output value indicative of the spindle's position.

3 15. (Previously presented) The device of Claim 14 wherein the magnitude of the  
4 digital output value  $R_{TA}$  is in substantial accordance with the equation:

$$5 \quad R_{TA} = \frac{3}{0.00016611111-0.00002555556(TA)} :$$

6  
7  
8 where: TA = the TA value at the position of the manually positionable  
9 means.

10  
11 16. (Previously presented) The device of Claim 2 including  
12 means for repeatedly sampling the analog measurement signal;  
13 means for obtaining the difference between (a) at least some of the sampled  
14 values and (b) the user-adjustable base value to obtain respective digital difference  
15 values.

16  
17 17. (Previously presented) The device of Claim 2 wherein the first non-linear gain  
18 applied by the gain-applying means is in substantial accordance with the relationship  
19 expressed by the equation:

$$20 \quad \text{Gain} = \frac{5000}{R_{TA} - 21087}$$

$$21 \quad \text{where } R_{TA} = \frac{3}{0.00016611111-0.00002555556(TA)} \text{ and}$$

22  
23  
24  
25  
26  
27  
28 TA = the TA value at the position of the manually positionable means.  
29  
30

1           18. (Previously presented) The device of Claim 2 wherein the second non-linear  
2 gain applied by the gain-applying means is in substantial accordance with the relationship  
3 expressed by the equation:

$$\text{Gain} = \frac{45450}{R_{TA} - 71941}$$

4  
5  
6  
7  
8  
9           where  $R_{TA} = \frac{3}{0.00016611111 - 0.00002555556(TA)}$  and  
10

11  
12           TA = the TA value at the position of the manually positionable means.  
13  
14

15           19. (Previously presented) The device of Claim 7 wherein the optical encoder is  
16 not affixed to the device, and further including communication means for communicating  
17 digital values generated by the optical encoder to the digital processing unit.  
18

19           20. (Previously presented) The device of Claim 7 wherein the device has both an  
20 affixed and a non-affixed optical encoder, and further including  
21 communication means for communicating digital values generated by the remote  
22 digital encoder to the digital processing unit, and  
23 means for deactivating the affixed digital encoder while remote digital values  
24 from the remote digital encoder are communicated to the digital processing unit.  
25  
26  
27  
28  
29

1           21. (Previously presented) The device of Claim 2 wherein the indicator circuit  
2 includes

3           a meter having a face, a coil for establishing a magnetic field when electric  
4 current flows through the coil, and an indicating needle deflected along said face by the  
5 magnetic field by an amount generally proportional to the amount of electric current  
6 through the coil;

7           means coupling an analog electrical signal representative of the processed  
8 measurement signal to the coil; and

9           optical transistor means shunting the coil to provide essentially a short circuit  
10 around the coil when the device is unpowered to prevent electromagnetically induced  
11 current in the meter coil from physical movement of the meter to cause sudden and off-  
12 scale needle movement that could damage the needle.

13  
14           22. (Previously presented) The device of Claim 2 wherein the resistance  
15 measuring circuit includes

16           first and second electrodes respectively coupled electrically to the external leads  
17 for electrical coupling to the living body so as to impose the resistance of the living body  
18 between the electrodes:

19           a voltage divider circuit adapted for coupling between a D.C. source voltage and a  
20 ground reference, the resistance sensing circuit comprising:

21           a first circuit leg having a series circuit connection between the D.C. source  
22 voltage and the ground reference (a) a first resistor, (b) said first and second electrodes  
23 and (c) a second resistor, said first and second electrodes being reasonably connected to  
24 said circuit.

25  
26           23. (Previously presented) The device of Claim 22 further including a bypass in  
27 said series circuit for selectively establishing a connection between said first and second  
28 resistors that bypasses the electrodes.

29  
30

1           24. (Previously presented) The device of Claim 23 wherein the bypass includes  
2           a jack having a pair of terminals respectively coupled to the first and second  
3           resistors for releasably connecting said electrodes via the jack in series circuit with the  
4           first and second resistors, and for electrically coupling said first and second resistors in  
5           series circuit when the electrodes are released from their circuit connection.

6  
7           25. (Previously presented) The device of Claim 24 including a third resistor, the  
8           jack electrically coupling the third resistor in series circuit between said first and second  
9           resistors when the electrodes are released from their circuit connection.